

# Whiteman Power Trowels — Specifications

|                   | Model               | No. Blades | Ring Dia.<br>in. (cm) | Power Source                       | Rotor RPM | Oper. Wt.<br>lb. (kg) | Ship Wt.<br>lb. (kg) |
|-------------------|---------------------|------------|-----------------------|------------------------------------|-----------|-----------------------|----------------------|
| <b>C-SERIES</b>   | <b>C-4-2-H</b>      | 4          | 24 (61)               | 2.5 HP Honda                       | 50-107    | 90 (41)               | 120 (54)             |
| <b>M-SERIES</b>   | <b>M-4-3BS</b>      | 4          | 30 (76)               | 3 HP Briggs & Stratton             | 60-125    | 131 (59)              | 171 (77)             |
|                   | <b>M-4-5-BS</b>     | 4          | 30 (76)               | 5 HP Briggs & Stratton             | 60-125    | 136 (62)              | 176 (80)             |
|                   | <b>M-4-4R</b>       | 4          | 30 (76)               | 5 HP Robin                         | 60-125    | 141 (64)              | 181 (82)             |
|                   | <b>M-4-4RM</b>      | 4          | 30 (76)               | 5 HP Robin, manual clutch          | 60-125    | 141 (64)              | 181 (82)             |
|                   | <b>M-4-5H</b>       | 4          | 30 (76)               | 5.5 HP Honda                       | 60-125    | 143 (65)              | 183 (83)             |
|                   | <b>M-4-5HM</b>      | 4          | 30 (76)               | 5.5 HP Honda, manual clutch        | 60-125    | 143 (65)              | 183 (83)             |
| <b>J-SERIES</b>   | <b>J-3-5BS</b>      | 3          | 36 (90)               | 5 HP Briggs & Stratton             | 60-125    | 139 (63)              | 179 (81)             |
|                   | <b>J-3-4R</b>       | 3          | 36 (90)               | 5 HP Robin                         | 60-125    | 144 (65)              | 184 (83)             |
|                   | <b>J-3-5H</b>       | 3          | 36 (90)               | 5.5 HP Honda                       | 60-125    | 146 (66)              | 186 (84)             |
|                   | <b>J-3-2E</b>       | 3          | 36 (90)               | 2 HP 115/230V 60 Hz 1Ø Electric    | 60-125    | 142 (64)              | 182 (83)             |
|                   | <b>J-3-2E-50</b>    | 3          | 36 (90)               | 2 HP 220V 50 Hz 1Ø Electric        | 60-125    | 142 (64)              | 182 (83)             |
|                   | <b>J-4-5BS</b>      | 4          | 36 (90)               | 5 HP Briggs & Stratton             | 60-125    | 143 (65)              | 183 (83)             |
|                   | <b>J-4-4R</b>       | 4          | 36 (90)               | 5 HP Robin                         | 60-125    | 148 (67)              | 188 (85)             |
|                   | <b>J-4-4RM</b>      | 4          | 36 (90)               | 5 HP Robin, manual clutch          | 60-125    | 148 (67)              | 188 (85)             |
|                   | <b>J-4-5H</b>       | 4          | 36 (90)               | 5.5 HP Honda                       | 60-125    | 150 (68)              | 190 (86)             |
|                   | <b>J-4-5HM</b>      | 4          | 36 (90)               | 5.5 HP Honda, manual clutch        | 60-125    | 150 (68)              | 190 (86)             |
|                   | <b>J-4-2E</b>       | 4          | 36 (90)               | 2 HP 115/230V 60 Hz 1Ø Electric    | 60-125    | 146 (66)              | 186 (84)             |
|                   | <b>J-4-2E-50</b>    | 4          | 36 (90)               | 2 HP 220V 50 Hz 1Ø Electric        | 60-125    | 146 (66)              | 186 (84)             |
| <b>B-SERIES</b>   | <b>B-3-8H</b>       | 3          | 46 (117)              | 8 HP Honda                         | 60-125    | 236 (107)             | 186 (130)            |
|                   | <b>B-4-8BS</b>      | 4          | 46 (117)              | 8 HP Briggs & Stratton             | 60-125    | 228 (103)             | 278 (126)            |
|                   | <b>B-4-7R</b>       | 4          | 46 (117)              | 7.5 HP Robin                       | 60-125    | 237 (107)             | 287 (130)            |
|                   | <b>B-4-7RM</b>      | 4          | 46 (117)              | 7.5 HP Robin, manual clutch        | 60-125    | 237 (107)             | 287 (130)            |
|                   | <b>B-4-8H</b>       | 4          | 46 (117)              | 8 HP Honda                         | 60-125    | 242 (110)             | 292 (132)            |
|                   | <b>B-4-8HM</b>      | 4          | 46 (117)              | 8 HP Honda, manual clutch          | 60-125    | 242 (110)             | 292 (132)            |
|                   | <b>B-4-2E</b>       | 4          | 46 (117)              | 2 HP, 115/230V, 1Ø Electric        | 108       | 179 (81)              | 229 (104)            |
| <b>E-SERIES</b>   | <b>E-4-1E-50</b>    | 4          | 36 (90)               | 1 HP 220V 50 Hz 1Ø Electric        | 25-52     | 112 (51)              | 152 (69)             |
|                   | <b>E-4-1EV</b>      | 4          | 36 (90)               | 1 HP 115V 60 Hz 1Ø Electric        | 30-62     | 112 (51)              | 152 (69)             |
|                   | <b>E-4-5H</b>       | 4          | 36 (90)               | 5.5 HP Honda                       | 27-62     | 127 (58)              | 167 (76)             |
| <b>HPL-SERIES</b> | <b>HPL-36-4-7R</b>  | 4          | 36 (90)               | 7.5 HP Robin                       | 55-118    | 166 (75)              | 206 (93)             |
|                   | <b>HPL-36-4-8H</b>  | 4          | 36 (90)               | 8 HP Honda                         | 55-118    | 171 (77)              | 211 (96)             |
|                   | <b>HPL-46-4-11H</b> | 4          | 46 (117)              | 11 HP Honda                        | 50-108    | 245 (111)             | 310 (141)            |
| <b>HPH-SERIES</b> | <b>HPH-36-4-7R</b>  | 4          | 36 (90)               | 7.5 HP Robin                       | 75-155    | 166 (75)              | 206 (93)             |
|                   | <b>HPH-36-4-8H</b>  | 4          | 36 (90)               | 8 HP Honda                         | 75-155    | 171 (77)              | 211 (96)             |
|                   | <b>HPH-46-4-11H</b> | 4          | 46 (117)              | 11 HP Honda                        | 65-140    | 250 (113)             | 310 (141)            |
| <b>HD-SERIES</b>  | <b>HD-48-4-11H</b>  | 4          | 48 (122)              | 11 HP Honda                        | 65-140    | 295 (134)             | 355 (161)            |
|                   | <b>HD-48-4-13H</b>  | 4          | 48 (122)              | 13 HP Honda, variable speed clutch | 35-180    | 315 (143)             | 365 (166)            |
| <b>S-SERIES</b>   | <b>S-60-13H</b>     | 4          | 60 (152)              | 13 HP Honda                        | 60-130    | 410 (186)             | 470 (213)            |